


Parts List							
ITEM	QTY	PART NUMBER	DESCRIPTION	ISSUE			
1	1	1TPE334B	Тор	001			
2	1	1ESE324B	RH Side	001			
3	1	1BKE334B	Rear Panel	002			
4	1	1ESE325B	LH Side	001			
5	1	1BSE334B	Base	001			
6	4	0FNM0120	M6 Hex Thin Head Pop-Nut	001			
7	14	90304003	Countersunk Rivet	001			

- 1. Rivet back and sides together using Cubio Csk rivets, spotweld down rear and side flanges.
- 2. Locate top and base and rivet into position using Cubio Csk rivets, spotweld across back and side flanges. INCLUDING ONE CENTERED SPOTWELD IN CHANNEL KNOCKOUTS.
- 3. Ensure housing is square then mig front corners internally -2 points in each corner as per diagram A.
- 4. Insert pop-nuts

hatt	Tolerances to be used unless otherwise stated.  DIM. <100   >100   >500   <1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >1000   >100								
DOLL	DIM.	<100	>100 <500	>500 <1000	>1000				
	TOL.	± 0.25	± 0.50	± 0.75	± 1.00				
www.bottltd.co.uk									

PRODUCT:
Wall Mounted Laptop Cabinet
DETAIL:

**DETAIL:**Housing Fabrication



DRN:LS DATE: 12/11/2014 CHKD:LS

ISS: 001 MOD. DATE:

SCALE: NTS DRG.
UNITS: MM NO.:

Bott Ltd 2002 This document, and the above information contained within it is the property of Bott Ltd. The document may not be reproduced or transmitted in any form or stored in any retreival system of any nature nor disclosed to any third party without the prior written permision of Bott Ltd.